



MULTIPLEX ALIGNMENT USING FM STEREO GENERATOR AND AUDIO OSCILLATOR

	SIGNAL GENERATOR	CONNECT SCOPE	ADJUST	REMARKS
1.	19KC to MPX Input.	Vert. input to pin 2 of V1, low side to ground.	A1	Adjust for maximum.
2.	"	Vert. input to pin 2 of V2, low side to ground.	A2	Adjust for maximum. Set scope to lock in 2 cycle waveform.
3.	"	Vert. input to point A3, low side to ground.	A3	Adjust for maximum 4 cycle waveform.
4.	67KC to MPX Input	"	A4, A5	Adjust for MINIMUM.
5.	20 KC to point B6 low side to ground.	Vert. input to point B6, low side to ground.	A6	Adjust for MINIMUM.

