



NUMBERS ASSIGNED TO COILS, SWITCHES, PLUGS, SOCKETS, AND TRANSFORMERS ARE TO FACILITATE CIRCUIT TRACING OR COMPONENT REPLACEMENT AND MAY NOT NECESSARILY BE FOUND ON THE UNIT.

SELECTOR SWITCH (M1) SHOWN IN "AUX" POSITION.  
SWITCH SEQUENCE:

1. AUX
2. TV
3. TUNER
4. MIC
5. TAPE HEAD
6. T8
7. RIAA
8. CDL
9. LON

1. Socket connections are shown as bottom views.
2. Measured values are from socket pin to common negative.
3. Nominal tolerance of component values makes possible a variation of ±15% in voltage and resistance readings.
4. All controls at minimum, proper output load connected.

RESISTANCE READINGS

ITEM	TUBE	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7	Pin 8	Pin 9
V1	ECC83 12AX7	1300K	1meg	4000Ω	25Ω	25Ω	1300K	1meg	2200Ω	25Ω
V2	ECC83 12AX7	1250K	0Ω	2200Ω	25Ω	25Ω	1100K	220K	2200Ω	25Ω
V3	ECC83 12AX7	10K	1meg	70K	25Ω	25Ω	1100K	100K	1000Ω	25Ω

1. MEASURED FROM PIN 4 OF POWER PLUG.