
LEFT
RIGHT
VOLTAGE GAIN + 47db @ 1 KC
PHONO SENSITIVITY IN "C" POSITION
+6db @ 1 KC
+2db
+22db
NOTE: −1db WITH RESPECT TO HIGH LEVEL INPUTS.
A1 PC-P-4 (Z-PC-P-4)
A2 PC-T-1 (Z-PC-T-1)
A3 PC-D-3 (Z-PC-D-4)
A101 PC-P-4 (Z-PC-P-4)
A102 PC-T-1 (Z-PC-T-1)
A103 PC-D-3 (Z-PC-D-4)
PREAMP P.C. BOARD
TONE CONTROL P.C. BOARD
DRIVER P.C. BOARD
RUMBLE
LOUD.
COMP.
BALANCE
BASS
TREBLE
SCRATCH
PHONO SENSITIVITY
EXTRA L
TUNER L
TAPE HEAD L
MAG. PHONO L
EXTRA R
TUNER R
TAPE HEAD R
MAG. PHONO R
FRONT 1
FRONT 2
INPUT
REAR 1
REAR 2
TAPE IN L
TAPE OUT L
TAPE IN R
TAPE OUT R
TAPE MONITOR
SELECTOR
FRONT
REAR
METER FUNCTION
POWER MONITOR
MSS-6 (150μA 1000Ω)
BIAS ADJ.
BAL. ADJ.
SPK'R IMPEDANCE 8-16Ω
2 AMP. INSTR. AGX-2
SPEAKERS
LEFT CHANNEL
RIGHT CHANNEL
H REMOTE
H MAIN
O
PHONES (FRONT PANEL)
POWER
INITIAL TEST SW.
ACCES. OUTLETS 105-120VAC. 250W. MAX.
105-120V 50-60~ AC. ONLY 25-150W @117.
F201 1¼ AMP. SLO-BLO
#1819 LAMP 28V (35MA)
+20V SOURCE
+25V SOURCE
+70V SOURCE
+70V
+25V
+20V
+70
REVISIONS
SYM | DESCRIPTION | DATE | APPR.
1 | ECO 1187 | 7-21-65
2 | ECO 1247 | 10-21-65
REV 2
LK-60-C1
METER FUNCTION
POS | FUNCTION
1. — BIAS LEFT CH. (SET TO "O").
2. — BAL. LEFT CH. (SET TO 1.5)
3. — POWER MONITOR
4. — BAL. RIGHT CH. (SET TO 1.5)
5. — BIAS RIGHT CH. (SET TO "O")
NOTE:
THE FOLLOWING CONTROLS IN LEFT CHANNEL ARE MECHANICALLY GANGED WITH IDENTICAL CONTROLS IN THE RIGHT CHANNEL.
1. INPUT
2. SELECTOR
3. SCRATCH FILTER
4. RUMBLE FILTER
5. PHONO SENSITIVITY
6. COMPENSATOR
7. TAPE
8. LOUDNESS
9. SPEAKERS
10. INIT. TEST SW.
HIGHEST SERIES NUMBERS
R21 R121 | R208 | C13 C113 | C207 | D2 D102 | D203 | T201
A1, A101 HIGHEST SERIES NO. R16, C8.
Z-PC-P-4
Q1 — Q-2N3391A (QA-12)
Q2 — Q-2N2926 or Q-2N3708 (QA-13)
Q3 — 2N2613 or 2N2058A.
A2, A102 HIGHEST SERIES NO. R12, C6.
Z-PC-T-1
Q1 — Q-2N2924 or Q-2N3710 (QA-14)
Q2 — Q-2N2925 or Q-2N3711 (QA-15)
A3, A103 HIGHEST SERIES NO. R19, C8, D1.
Z-PC-D-4
* Q1 — QA-10 (GREEN DOT)
Q2 — QA-9 or 2N398B
* Q3 — QA-10 (GN or BLUE DOT)
* Q4 — QA-10 (GN, BLUE or RED DOT)
(* SELECTED 2N3053).
SELECTOR
POS. | FUNCTION
1 — BAL. L.
2 — BAL. R.
3 — MONO
4 — STEREO
5 — REV. STEREO
6 — L. INPUT
7 — R. INPUT
INPUT
POS. | FUNCTION
1 — TAPE HD.
2 — PHONO
3 — TUNER
4 — EXTRA
UNLESS OTHERWISE SPECIFIED:
1. RESISTORS IN OHMS & ½ WATT.
2. CAPACITORS IN MFD.
3. VOLTS D.C. ± 15% MEASURED WITH 20KΩ/V.V.O.M. NO SIGNAL & 117V LINE.
4. GAINS ± 2db WITH A.C.V.T.V.M.
5. ARROWS ON POTS INDICATE C.W. ROTATION.
DATE 4-8-65
DRAF. KESSLER CASSIDY
CH.
ENG LANGMUIR
PROD.
H.H.SCOTT, INC. MAYNARD, MASS
CIRCUIT DIAGRAM
SCALE: ~
SHEET 1 OF 1
DWG. SIZE D
LK-60-C1
REV 2